




Torque(N·m)



| Power Pin Assignment | |
|----------------------|--------------|
| Signal | AMP-172167-1 |
| U | 3 |
| V | 2 |
| W | 1 |
| ≡ | 4 |

Connector A



Connector B

| Encoder Pin Assignment | | |
|------------------------|-----------|----------------|
| Function | Signal | AMP 1-172169-9 |
| Power | 5V | 1 |
| | 0V | 2 |
| Incremental Signal | SL + | 3 |
| | SL - | 4 |
| | TBD | 5 |
| | TBD | 6 |
| | MA + | 7 |
| | MA - | 8 |
| shielding | shielding | 9 |

Rate Power : 100W
 Driver Input Voltage : 220V
 Rated Torque : 0.32N·m
 Rated Speed : 3000 rpm
 Rated Current : 0.9A(Arms)
 Encoder : 17-bit Incremental
 Brake : No
 Shaft : Round
 Oil seal : No

| ITEM | DATE | MODIFIED | DESCRIPTION | CHK | APPD |
|------|------|----------|-------------|-----|------|
| | | | | | |

| NAME | DWG NO | SHEET | TYPE | LS-100W | DATE |
|----------------|---------|-------|---------|--------------|------------|
| AC SERVO MOTOR | AC02049 | A1 | 1-1 | CUSTOMER | 2014.03.15 |
| | | | | DRN | 邱婉容 |
| | | | SCALE | 1 : X | CHK |
| | | | PART NO | FRLS10206A4A | APPD |
| | | | | Hsin-An | |

HIWIN® MIKROSYSTEM CORP.