



Connector A


| Power Pin Assignment | |
|----------------------|--------------|
| Signal | AMP-172167-1 |
| U | 3 |
| V | 2 |
| W | 1 |
| ≡ | 4 |



Connector B

| Encoder Pin Assignment | | |
|------------------------|-----------|----------------|
| Function | Signal | AMP 1-172169-9 |
| Power | 5V | 1 |
| | 0V | 2 |
| Incremental Signal | SL + | 3 |
| | SL - | 4 |
| | TBD -- | 5 |
| | TBD -- | 6 |
| | MA + | 7 |
| | MA - | 8 |
| Shielding | Shielding | 9 |

Rate Power : 400W
Driver Input Voltage : 220V
Rated Torque : 1.27N-m
Rated Speed : 3000 rpm
Rated Current : 2.5A(Arms)
Encoder : DA-235-17(HIWIN 17-bit Incremental)
Brake : No
Shaft : Key,Center tap
Oil seal : No



Key Size

| NAME | DWG NO | SHEET | TYPE | LS400W | DATE | 2014.03.15 |
|----------------|---------|-------|------|----------|--------------|------------|
| AC SERVO MOTOR | AC42035 | A2 | 1-1 | CUSTOMER | DRN | 邱婉容 |
| | | | | SCALE | 1 : X | CHK 鄭立巍 |
| | | | | PART NO | FRLS4020606C | APPD 江新安 |

HIWIN® MIKROSYSTEM CORP.

| ITEM | DATE | MODIFIED | DESCRIPTION | APPD |
|------|------------|----------|-------------|------------------|
| 1 | 2014.07.10 | 邱婉容 | 1.新增尺寸26 | U120B-ECN-140407 |