

07df0a0e0625390111015301eb0042a3

A

B




C

D



E

F

G





07df0a0e0625390111015301eb0042a3



Connector A


Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
≡	4



Connector B

Encoder Pin Assignment		
Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SL +	3
	SL -	4
	TBD --	5
	TBD --	6
	MA +	7
	MA -	8
Shielding	Shielding	9

Rate Power : 400W
Driver Input Voltage : 220V
Rated Torque : 1.27N-m
Rated Speed : 3000 rpm
Rated Current : 2.5A(Arms)
Encoder : DA-235-17(HIWIN 17-bit Incremental)
Brake : No
Shaft : Key,Center tap
Oil seal : Yes



Key Size

ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	LS400W	DATE	2015.02.26
AC SERVO MOTOR	AC42108	A1	1-1	CUSTOMER	DRN	邱婉容
HIWIN® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 林政穎
				PART NO	FRLS4020606D	APPD 鄭立巍