






07df031101161d01b90022d5010053c1




Brake Pin Assignment	
Signal	WPS3102A14S-7P-R
B+	A
B-	C

Connector C



Power Pin Assignment	
Signal	WPS3102A18-10P-R
U	A
V	B
W	C
≡	D


Connector A



Encoder Pin Assignment		
Function	Signal	WPS3102A18-1P-R
Power	5V	A
	0V	B
Incremental Signal/ Hall Signal	A/U +	C
	A/U -	D
	B/V --	E
	B/V --	F
	Z/W +	G
Shielding	Z/W -	H
	Shielding	I

Connector B

Rate Power : 2000W
Driver Input Voltage : 220V
Rated Torque : 9.55N-m
Rated Speed : 2000 rpm
Rated Current : 11A(Arms)
Encoder : 13-bit Incremental
Brake : Yes
Shaft : Key,Center tap
Oil seal : No



Key Size

NAME	DWG NO	SHEET	TYPE	MM2KW	DATE	2014.03.15
AC SERVO MOTOR	AC32023	A2	1-1	CUSTOMER	DRN	邱婉容
HIWIN® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMM2K2B513C	APPD 江新安

ITEM	DATE	MODIFIED	DESCRIPTION	APPD
1	2014.07.02	邱婉容	新增尺寸50	U120B-ECN -140407