






HIWIN CONFIDENTIAL

機密文件未經許可，嚴禁複製



| Power Pin Assignment | |
|----------------------|------------------|
| Signal | WPS3102A18-10P-R |
| U | A |
| V | B |
| W | C |
| ⏏ | D |


Connector A



| Encoder Pin Assignment | | |
|------------------------|-----------|-----------------|
| Function | Signal | WPS3102A18-1P-R |
| Power | 5V | A |
| | 0V | B |
| Incremental Signal | SL + | C |
| | SL - | D |
| | TBD -- | E |
| | TBD -- | F |
| | MA + | G |
| | MA - | H |
| Shielding | Shielding | I |

Connector B

Rate Power : 2000W
 Driver Input Voltage : 220V
 Rated Torque : 9.55N-m
 Rated Speed : 2000 rpm
 Rated Current : 11A(Arms)
 Encoder : DA-235-17(HIWIN 17-bit Incremental)
 Brake : No
 Shaft : Key, Center tap
 Oil seal : No



Key Size

| ITEM | DATE | MODIFIED | DESCRIPTION | APPD |
|------|------------|----------|-------------|------------------|
| 1 | 2014.07.02 | 邱婉容 | 新增尺寸50 | U120B-ECN-140407 |

| NAME | DWG NO | SHEET | TYPE | MM2KW | DATE | 2014.03.15 |
|----------------------------------|---------|-------|------|----------|--------------|------------|
| AC SERVO MOTOR | AC32018 | A2 | 1-1 | CUSTOMER | DRN | 邱婉容 |
| HIWIN ® MIKROSYSTEM CORP. | | | | SCALE | 1 : X | CHK 鄭立巍 |
| | | | | PART NO | FRMM2K20613C | APPD 江新安 |