


Connector A


A : Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
≡	4



Connector B

B : Encoder Pin Assignment		
Function	Signal	AMP-172169-1
Power	5V	1
	0V	2
Incremental Signal/ Hall Signal	A/U +	3
	A/U -	4
	B/V +	5
	B/V -	6
	Z/W +	7
	Z/W -	8
Shielding	Shielding	9

Rate Power : 200W  
Driver Input Voltage : 220V  
Rated Torque : 0.64N-m  
Rated Speed : 3000 rpm  
Rated Current : 1.7A(Arms)  
Moment of Inertia of rotor : 0.24 Kg-m<sup>2</sup> (\*10<sup>-4</sup>)  
Allowable Load Inertia Ratio : 10 times or less  
Encoder : 13-bit Incremental  
Brake : No  
Shaft : Key, Center tap  
Oil seal : No



Key Size

NAME	DWG NO	SHEET	TYPE	MS-200W	DATE	2018.08.27
AC SERVO MOTOR	AC42360	A1	1-1	CUSTOMER	DRN	周孟儒
HIWIN® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 曾緯凱
				PART NO	FRMS2B20506C	APPD 林政穎

ITEM	DATE	MODIFIED	DESCRIPTION	APPD