




Torque(N-m)



Connector A


A : Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
≡	4



Connector B

B : Encoder Pin Assignment		
Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SD +	7
	SD -	8
Shielding	Shielding	9
Battery	VB	5
	GND	6

Rate Power : 200W  
 Driver Input Voltage : 220V  
 Rated Torque : 0.64N-m  
 Rated Speed : 3000 rpm  
 Rated Current : 1.7A(Arms)  
 Moment of Inertia of rotor : 0.24 Kg-m<sup>2</sup> (\*10<sup>-4</sup>)  
 Allowable Load Inertia Ratio : 10 times or less  
 Encoder : 17-bit Absolute  
 Brake : No  
 Shaft : Key, Center tap  
 Oil seal : No



Key Size

NAME	DWG NO	SHEET	TYPE	MS200W	DATE	2018.03.09
AC SERVO MOTOR	AC42306	A1	1-1	CUSTOMER	DRN	周孟儒
HIWIN® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 林政穎
				PART NO	FRMS2B20406C	APPD 鄭立巍

ITEM	DATE	MODIFIED	DESCRIPTION	APPD