



### GDK80-24Z/1.5

#### Wiring description

Pin	4-pin socket
1	U frequency converter phase
2	V frequency converter phase
3	W frequency converter phase
4	Wiring ground

Rated power	1.5 kw
Rated voltage	380 V
Rated rotating speed	24000 r/min
Rated frequency	400 Hz
Rated current	3.0 A
ER nut	ER-16
Bearing model	7004C×2 7001C×2
Bearing lubrication	Grease lubrication
Weight	6 KG
Rotating mode	anticlockwise from the shaft extension end

#### Special warning:

1. The electric main shaft shall be installed at the clamped position; otherwise the bearing will be easily damaged!
2. The compressed air shall be dry and clean, and the filtering accuracy shall be 0.1 micron! Atmospheric pressure is 0.1- 0.2MPa, and the air seal shall be normally open. It is recommended to use the two-level filtration, with the filtration accuracy of 0.5 micron/0.1 micron respectively, and the air filter shall have automatic discharge device.

						380V			
						Outline diagram			
						GDK80-24Z/1.5			
Marks	Number of places	Zoning	Modified document number	Signature	Date	Phase mark		Weight	Scale
Designed by			Standardized by						
Reviewed by									
Processed by			Approved by			Total page(s)		Page	