



Power Pin Assignment	
Signal	WPS3102A18-10P-R
U	A
V	B
W	C
⏏	D



Encoder Pin Assignment		
Function	Signal	WPS3102A18-1P-R
Power	5V	A
	0V	B
Serial data Signal	SD +	G
	SD -	H
Shielding	Shielding	I



Rated Power : 1000W
 Drive Input Voltage : 220VAC
 Rated Torque : 4.77N-m
 Rated Speed : 2000 rpm
 Rated Current : 5.1A(Arms)
 Moment of Inertia : 7.2 Kg-m² (*10⁻⁴)
 Encoder : 23-bit Incremental
 Brake : No
 Shaft : Key, Center tap
 Oil seal : Yes

ITEM	DATE	MODIFIED	DESCRIPTION	ECN NO.	CHK	APPD

NAME	DWG NO	SHEET	TYPE	EM1-A-M-1K-2-0-E-0-D	DATE	2019.09.24
AC SERVO MOTOR	AC32133	A1	1-1	CUSTOMER	DRN	周孟儒
HIWIN® MIKROSYSTEM CORP.			SCALE	1 : X	CHK	黎振安
			PART NO	FRE051K2E012	APPD	林政穎