




Torque(N·m)



Connector A


Power Pin Assignment	
Signal	AMP-172168-1
U	3
V	2
W	1
±	4
B+	5
B-	6



Connector B

Encoder Pin Assignment		
Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SL +	3
	SL -	4
	TBD --	5
	TBD --	6
MA +	7	
MA -	8	
shielding	shielding	9

Rate Power : 100W  
 Driver Input Voltage : 220V  
 Rated Torque : 0.32N·m  
 Rated Speed : 3000 rpm  
 Rated Current : 0.9A(Arms)  
 Encoder : 17-bit Incremental  
 Brake : Yes  
 Shaft : Key,Center tap  
 Oil seal : Yes



Key Size

NAME	DWG NO	SHEET	TYPE	LS100W	DATE
AC SERVO MOTOR	AC02104	A1	1-1		2016.05.25
CUSTOMER				DRN	林政穎
SCALE				CHK	
PART NO	FRLS102B6A4D	APPD		鄭立巍	

HIWIN® MIKROSYSTEM CORP.