



Torque(N·m)




Power Pin Assignment

Signal	AMP-172168-1
U	3
V	2
W	1
±	4
B+	5
B-	6

Connector A

Rate Power : 100W
 Driver Input Voltage : 220V
 Rated Torque : 0.32N·m
 Rated Speed : 3000 rpm
 Rated Current : 0.9A(Arms)
 Encoder : 17-bit Incremental
 Brake : Yes
 Shaft : Round
 Oil seal : No



Encoder Pin Assignment

Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SL +	3
	SL -	4
	TBD --	5
	TBD --	6
	MA +	7
	MA -	8
shielding	shielding	9

Connector B

NAME	DWG NO	SHEET	TYPE	LS-100W	DATE
AC SERVO MOTOR	AC02050	A1	1-1		2014.03.15
			CUSTOMER		DRN 邱婉容
			SCALE	1 : X	CHK 盧品勳
			PART NO	FRLS102B6A4A	APPD Hsin-An

HIWIN® MIKROSYSTEM CORP.