





Torque(N·m)




Power Pin Assignment		
Signal	AMP-172167-1	
U	3	
V	2	
W	1	
≡	4	

Connector A



Encoder Pin Assignment		
Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SL +	3
	SL -	4
	TBD --	5
	TBD --	6
	MA +	7
	MA -	8
shielding	shielding	9



Key Size

Rate Power : 100W
 Driver Input Voltage : 220V
 Rated Torque : 0.32N·m
 Rated Speed : 3000 rpm
 Rated Current : 0.9A(Arms)
 Encoder : 17-bit Incremental
 Brake : No
 Shaft : Key,Center tap
 Oil seal : No

NAME	DWG NO	SHEET	TYPE	LS-100W	DATE
AC SERVO MOTOR	AC02051	A1	1-1		2014.03.15
CUSTOMER				DRN	邱婉容
SCALE				CHK	盧品勳
PART NO	FRLS10206A4C			APPD	Hsin-An

HIWIN® MIKROSYSTEM CORP.

ITEM	DATE	MODIFIED	DESCRIPTION	CHK	APPD