



Connector A

Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
≡	4



Connector B

Encoder Pin Assignment			
Function	Signal		AMP 1-172169-9
Power	5V		1
	0V		2
Incremental Signal	SL	+	3
	SL	-	4
	TBD	--	5
	TBD	--	6
	MA	+	7
	MA	-	8
Shielding	Shielding		9

Rate Power : 400W  
Driver Input Voltage : 220V  
Rated Torque : 1.27N-m  
Rated Speed : 3000 rpm  
Rated Current : 2.5A(Arms)  
Encoder : DA-235-17(HIWIN 17-bit Incremental)  
Brake : No  
Shaft : Round  
Oil seal : Yes

NAME	DWG NO	SHEET	TYPE	LS400W	DATE	2015.02.26
AC SERVO MOTOR	AC42106	A1	1-1	CUSTOMER	DRN	邱婉容
HIWIN® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 林政穎
				PART NO	FRLS4020606B	APPD 鄭立巍

ITEM	DATE	MODIFIED	DESCRIPTION	APPD