



Connector A

Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
\equiv	4



Connector B

Encoder Pin Assignment			
Function	Signal		AMP 1-172169-9
Power	5V		1
	0V		2
Incremental Signal	SL	+	3
	SL	-	4
	TBD	--	5
	TBD	--	6
	MA	+	7
	MA	-	8
Shielding	Shielding		9

Rate Power : 400W
Driver Input Voltage : 220V
Rated Torque : 1.27N-m
Rated Speed : 3000 rpm
Rated Current : 2.5A(Arms)
Encoder : DA-235-17(HIWIN 17-bit Incremental)
Brake : No
Shaft : Round
Oil seal : No

ITEM	DATE	MODIFIED	DESCRIPTION	APPD
1	2014.07.10	邱婉容	1.新增尺寸26	U120B-ECN-140407

NAME	DWG NO	SHEET	TYPE	LS400W	DATE	2014.03.15
AC SERVO MOTOR	AC42033	A2	1-1	CUSTOMER	DRN	邱婉容
HIWIN® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRLS4020606A	APPD 江新安