


Power Pin Assignment	
Signal	WPS3102A18-10P-R
U	A
V	B
W	C
⏏	D


Connector A



Encoder Pin Assignment		
Function	Signal	WPS3102A18-1P-R
Power	5V	A
	0V	B
Incremental Signal	SL +	C
	SL -	D
	TBD --	E
	TBD --	F
	MA +	G
	MA -	H
Shielding	Shielding	I

Connector B

Rate Power : 1000W
 Driver Input Voltage : 220V
 Rated Torque : 4.77N-m
 Rated Speed : 2000 rpm
 Rated Current : 5.1A(Arms)
 Encoder : DA-235-17(HIWIN 17-bit Incremental)
 Brake : No
 Shaft : Key, Center tap
 Oil seal : No



Key Size

ITEM	DATE	MODIFIED	DESCRIPTION	APPD
1	2014.07.03	邱婉容	新增尺寸50	U120B-ECN-140407

NAME	DWG NO	SHEET	TYPE	MM1KW	DATE	2014.03.18
AC SERVO MOTOR	AC32016	A2	1-1	CUSTOMER	DRN	邱婉容
HIWIN ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMM1K20613C	APPD 江新安