



Brake Pin Assignment	
Signal	WPS3102A14S-7P-R
B+	A
B-	C

Connector C



Power Pin Assignment	
Signal	WPS3102A18-10P-R
U	A
V	B
W	C
⏏	D

Connector A



Encoder Pin Assignment		
Function	Signal	WPS3102A18-1P-R
Power	5V	A
	0V	B
Incremental Signal	SL	+
	SL	-
	TBD	--
	TBD	--
	MA	+
Shielding	MA	-
	Shielding	I

Connector B

Rate Power : 1000W
 Driver Input Voltage : 220V
 Rated Torque : 4.77N-m
 Rated Speed : 2000 rpm
 Rated Current : 5.1A(Arms)
 Encoder : DA-235-17(HIWIN 17-bit Incremental)
 Brake : Yes
 Shaft : Round
 Oil seal : No

1	2014.07.03	邱婉容	新增尺寸50	U120B-ECN-140407
ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MM1KW	DATE	2014.03.15
AC SERVO MOTOR	AC32013	A2	1-1	CUSTOMER	DRN	邱婉容
HIWIN ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMM1K2B613A	APPD 江新安