


Power Pin Assignment	
Signal	WPS3102A18-10P-R
U	A
V	B
W	C
⏏	D

Connector A



Encoder Pin Assignment			
Function	Signal	WPS3102A18-1P-R	
Power	5V	A	
	0V	B	
Battery	VB	E	
	GND	F	
Incremental Signal	SD	+	G
	SD	-	H
Shielding	Shielding	I	

Connector B

Rate Power : 1000W
Driver Input Voltage : 220V
Rated Torque : 4.77N-m
Rated Speed : 2000 rpm
Rated Current : 5.1A(Arms)
Encoder : 17-bit Absolute
Brake : No
Shaft : Round
Oil seal : Yes

ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MM1KW	DATE	2015.01.16
AC SERVO MOTOR	AC32048	A1	1-1	CUSTOMER	DRN	邱婉容
HIWIN ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMM1K20413B	APPD 江新安