



Brake Pin Assignment		
Signal	WPS3102A14S-7P-R	
B+	A	
B-	C	

Connector C




Power Pin Assignment		
Signal	WPS3102A18-10P-R	
U	A	
V	B	
W	C	
⏏	D	

Connector A



Encoder Pin Assignment			
Function	Signal	WPS3102A18-1P-R	
Power	5V	A	
	0V	B	
Battery	VB	E	
	GND	F	
Incremental Signal	SD +	G	
	SD -	H	
Shielding	Shielding	I	

Connector B



Key Size

Rate Power : 1000W  
Driver Input Voltage : 220V  
Rated Torque : 4.77N-m  
Rated Speed : 2000 rpm  
Rated Current : 5.1A(Arms)  
Encoder : 17-bit Absolute  
Brake : Yes  
Shaft : Key,Center tap  
Oil seal : No

ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MM1KW	DATE	2015.01.16
AC SERVO MOTOR	AC32053	A1	1-1	CUSTOMER	DRN	邱婉容
<b>HIWIN</b> ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMM1K2B413C	APPD 江新安