


Power Pin Assignment	
Signal	WPS3102A18-10P-R
U	A
V	B
W	C
⏏	D

Connector A



Encoder Pin Assignment			
Function	Signal		WPS3102A18-1P-R
Power	5V		A
	0V		B
Incremental Signal	SL	+	C
	SL	-	D
	TBD	--	E
	TBD	--	F
	MA	+	G
	MA	-	H
Shielding	Shielding		I

Connector B

Rate Power : 1000W
Driver Input Voltage : 220V
Rated Torque : 4.77N-m
Rated Speed : 2000 rpm
Rated Current : 5.1A(Arms)
Encoder : DA-235-17(HIWIN 17-bit Incremental)
Brake : No
Shaft : Round
Oil seal : Yes

ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MM1KW	DATE	2015.01.12
AC SERVO MOTOR	AC32040	A1	1-1	CUSTOMER	DRN	邱婉容
HIWIN ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMM1K20613B	APPD 江新安