



Brake Pin Assignment	
Signal	WPS3102A14S-7P-R
B+	A
B-	C

Connector C




Power Pin Assignment	
Signal	WPS3102A18-10P-R
U	A
V	B
W	C
⏏	D

Connector A



Encoder Pin Assignment		
Function	Signal	WPS3102A18-1P-R
Power	5V	A
	0V	B
Incremental Signal	SL +	C
	SL -	D
	TBD --	E
	TBD --	F
	MA +	G
Shielding	MA -	H
	Shielding	I

Connector B



Key Size

Rate Power : 1000W
Driver Input Voltage : 220V
Rated Torque : 4.77N-m
Rated Speed : 2000 rpm
Rated Current : 5.1A(Arms)
Encoder : DA-235-17(HIWIN 17-bit Incremental)
Brake : Yes
Shaft : Key, Center tap
Oil seal : Yes

ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MM1KW	DATE	2015.01.12
AC SERVO MOTOR	AC32042	A1	1-1	CUSTOMER	DRN	邱婉容
HIWIN ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMM1K2B613D	APPD 江新安