


Power Pin Assignment	
Signal	WPS3102A18-10P-R
U	A
V	B
W	C
⏏	D


Connector A



Encoder Pin Assignment		
Function	Signal	WPS3102A18-1P-R
Power	5V	A
	0V	B
Battery	VB	E
	GND	F
Incremental Signal	SD +	G
	SD -	H
Shielding	Shielding	I

Connector B

Rate Power : 2000W
Driver Input Voltage : 220V
Rated Torque : 9.55N-m
Rated Speed : 2000 rpm
Rated Current : 11A(Arms)
Encoder : 17-bit Absolute
Brake : No
Shaft : Key,Center tap
Oil seal : Yes



Key Size

ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MM2KW	DATE	2015.01.16
AC SERVO MOTOR	AC32058	A1	1-1	CUSTOMER	DRN	邱婉容
HIWIN ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMM2K20413D	APPD 江新安