




A : Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
⏏	4



B : Encoder Pin Assignment		
Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SL +	3
	SL -	4
	TBD --	5
	TBD --	6
	MA +	7
	MA -	8
Shielding	Shielding	9

Rate Power : 50W
Driver Input Voltage : 220V
Rated Torque : 0.16N-m
Rated Speed : 3000 rpm
Rated Current : 0.9A(Arms)
Encoder : DA-235-17(HIWIN 17-bit Incremental)
Brake : No
Shaft : Key, Center tap
Oil seal : No



ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MS50W	DATE	2015.01.15
AC SERVO MOTOR	AC52032	A1	1-1	CUSTOMER	DRN	邱婉容
HIWIN® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMS0520604C	APPD 江新安