




Connector A

A : Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
	4



Connector B

B : Encoder Pin Assignment			
Function	Signal		AMP 1-172169-9
Power	5V		1
	0V		2
Incremental Signal	SD	+	7
	SD	-	8
Shielding	Shielding		9
Battery	VB		5
	GND		6

Rate Power : 50W
Driver Input Voltage : 220V
Rated Torque : 0.16N-m
Rated Speed : 3000 rpm
Rated Current : 0.9A(Arms)
Encoder : 17-bit Absolute
Brake : No
Shaft : Round
Oil seal : No

NAME	DWG NO		SHEET	TYPE	MS50W	DATE	2015.01.15
AC SERVO MOTOR	AC52038	A1	1-1	CUSTOMER		DRN	邱婉容
 HIWIN ® <i>MIKROSYSTEM CORP.</i>				SCALE	1 : X	CHK	鄭立巍
				PART NO	FRMS0520404A	APPD	江新安