



Connector A


A : Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
≡	4



Connector B

B : Encoder Pin Assignment		
Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SD +	7
	SD -	8
Shielding	Shielding	9
Battery	VB	5
	GND	6

Rate Power : 50W  
 Driver Input Voltage : 220V  
 Rated Torque : 0.16N-m  
 Rated Speed : 3000 rpm  
 Rated Current : 0.9A(Arms)  
 Encoder : 17-bit Absolute  
 Brake : No  
 Shaft : Key, Center tap  
 Oil seal : Yes



Key Size

NAME	DWG NO	SHEET	TYPE	MS50W	DATE	2015.01.15
AC SERVO MOTOR	AC52025	A1	1-1	CUSTOMER	DRN	邱婉容
<b>HIWIN</b> ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMS0520404D	APPD 江新安

ITEM	DATE	MODIFIED	DESCRIPTION	APPD