






Torque(N-m)



Connector A

A : Power Pin Assignment

Signal	AMP-172168-1
U	3
V	2
W	1
⏏	4
B+	5
B-	6



Connector B

B : Encoder Pin Assignment

Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SL +	3
	SL -	4
	TBD --	5
	TBD --	6
	MA +	7
	MA -	8
Shielding	Shielding	9

Rate Power : 50W

Driver Input Voltage : 220V

Rated Torque : 0.16N-m

Rated Speed : 3000 rpm


Rated Current : 0.9A(Arms)

Encoder : DA-235-17(HIWIN 17-bit Incremental)

Brake : Yes

Shaft : Key, Center tap

Oil seal : Yes



Key Size

ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MS50W	DATE	2015.01.15
AC SERVO MOTOR	AC52037	A1	1-1	CUSTOMER	DRN	邱婉容
<b>HIWIN</b> ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMS052B604D	APPD 江新安