


Connector A


A : Power Pin Assignment	
Signal	AMP-172168-1
U	3
V	2
W	1
\varnothing	4
B+	5
B-	6



Connector B

B : Encoder Pin Assignment		
Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SD +	7
	SD -	8
Shielding	Shielding	9
Battery	VB	5
	GND	6

Rate Power : 50W
Driver Input Voltage : 220V
Rated Torque : 0.16N-m
Rated Speed : 3000 rpm
Rated Current : 0.9A(Arms)
Encoder : 17-bit Absolute
Brake : Yes
Shaft : Key, Center tap
Oil seal : No



Key Size

NAME	DWG NO	SHEET	TYPE	MS50W	DATE	2015.01.15
AC SERVO MOTOR	AC52028	A1	1-1	CUSTOMER	DRN	邱婉容
HIWIN® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMS052B404C	APPD 江新安

ITEM	DATE	MODIFIED	DESCRIPTION	APPD