






Torque(N-m)




A : Power Pin Assignment	
Signal	AMP-172167-1
U	3
V	2
W	1
$\equiv$	4



B : Encoder Pin Assignment		
Function	Signal	AMP 1-172169-9
Power	5V	1
	0V	2
Incremental Signal	SL +	3
	SL -	4
	TBD -	5
	TBD -	6
	MA +	7
	MA -	8
Shielding	Shielding	9

Rate Power : 100W  
Driver Input Voltage : 220V  
Rated Torque : 0.32N-m  
Rated Speed : 3000 rpm  
Rated Current : 0.9A(Arms)  
Encoder : DA-235-17(HIWIN 17-bit Incremental)  
Brake : No  
Shaft : Key, Center tap  
Oil seal : Yes



ITEM	DATE	MODIFIED	DESCRIPTION	APPD

NAME	DWG NO	SHEET	TYPE	MS100W	DATE	2015.01.14
AC SERVO MOTOR	AC52018	A1	1-1	CUSTOMER	DRN	邱婉容
<b>HIWIN</b> ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK 鄭立巍
				PART NO	FRMS1020604D	APPD 江新安