




### Connector A


A : Power Pin Assignment	
Signal	AMP-172168-1
U	3
V	2
W	1
	4
B+	5
B-	6



### Connector B

B : Encoder Pin Assignment			
Function	Signal		AMP 1-172169-9
Power	5V		1
	0V		2
Incremental Signal	SD	+	7
	SD	-	8
Shielding	Shielding		9
Battery	VB		5
	GND		6

Rate Power : 100W  
Driver Input Voltage : 220V  
Rated Torque : 0.32N-m  
Rated Speed : 3000 rpm  
Rated Current : 0.9A(Arms)  
Encoder : 17-bit Absolute  
Brake : Yes  
Shaft : Key,Center tap  
Oil seal : No



NAME	DWG NO		SHEET	TYPE	MS100W	DATE	2015.01.14
AC SERVO MOTOR	AC52013	A1	1-1	CUSTOMER		DRN	邱婉容
 <b>HIWIN</b> ® MIKROSYSTEM CORP.				SCALE	1 : X	CHK	鄭立巍
				PART NO	FRMS102B404C	APPD	江新安